Bluetooth® Portable Generator





Power that's smart.

Monitor your generator from inside your home, when and where you need it.

StatStation Wireless

Download the StatStation® Wireless app to stay connected to the new Briggs & Stratton® 8000 watt Elite Series" portable generator with Bluetooth connectivity. From fuel consumption and power availability to maintenance notifications you can now monitor it all from the comfort of your home.



Elite Series[™] Portable Generator

Bluetooth[®] enabled

Download the StatStation® Wireless app and monitor your generator from inside.

- Total power used
- Hours until empty
- Total unit hours
- Maintenance reminders

Key electric start

Provides fast, effortless starting.

Up to 9 hours of run time³

7.5 gallon fuel tank for less refueling.

12" Never go flat wheels

For easy mobility.

Series	Elite Series™
Model #	030679
Running Watts ¹	8000
Starting Watts ²	10000
Volts	120/240
Engine	
Engine	Briggs & Stratton®
CC	420
Outlets	
	(4) 120V-20A GFCI
	(1) 120/240V, 30A Locking
Dimensions (L x W x H)	28.35" x 30.51" x 29.13"
Weight	224 lbs
Limited Warranty ⁴	36 Months Consumer 12 Months Commercial

Features	
Fuel Tank Capacity	7.5 Gallons
Run Time	9 Hours (50% Load)
Alternator	Power Surge™
Starting	Electric / Recoil
Low Oil Shutdown	•
Automatic Voltage Regulation	
Muffler	Lo-Tone™
Spark Arrestor	•
Bluetooth®	•
Fuel Gauge	•
Hour Meter	•
Rubber Outlet Covers	•
Wheels	12"
Engine Oil Included	Oil in crank case





BRIGGS & STRATTON CORPORATION Post Office Box 702 Milwaukee, WI 53201 USA (414) 259-5333



Copyright ©2017. All rights reserved.

 $^{^{\}rm I}$ Generator certified in accordance with CSA (Canadian Standards Association) standard C22.2 No. 100-14, Motors and Generators.

 $^{^2}$ Starting Watts is the maximum current that can momentarily be supplied when starting a motor, multiplied by the generator's rated voltage.

³ At 50% load.

 $^{^{\}rm 4}$ For full warranty details visit briggsandstratton.com.